

## Primary Current Injection Test Set

### RDSL-82 Series 2000A&5000A&6000A&10000A



**2000A**



**5000A**



**6000A**



**10000A**

**RDSL-82 series Primary Current Injection Test Set** is the necessary equipment in the electrical debugging of all walks of life. It is used in power plants, power transformation and distribution stations, electrical equipment manufacturers, scientific research, laboratories and other units. It belongs to short-time or intermittent working system. It has the characteristics of small volume, light weight, good performance, convenient use and maintenance.



### Product features

1. Two ammeters, large and small range monitoring.
2. Indicator light indication, button operation, simple operation.



### Product specifications and technical parameters

Picture				
Model	<b>RDSL-82-2000A</b>	<b>RDSL-82-5000A</b>	<b>RDSL-82-6000A</b>	<b>RDSL-82-10000A</b>
Rated capacity	12KVA	<b>30kVA</b>	<b>36kVA</b>	<b>60kVA</b>
Input voltage	380V	AC 380V, 50Hz	AC 380V, 50Hz	AC 380V, 50Hz

Input current	31.5A	79A	95A	158A
Output voltage	6V	6V	6V	6V
Output current:	2000A	5000A	6000A	10000A
Overall dimension	L * W * H: 600 * 430 * 760			
Structural type		Split type	Split type	Split type

Note:

- The Primary Current Injection Test Set capacity is designed based on a 5-minute short time working system. If it is used for intermittent work, the power-on time should be less than 2.5 minutes, and the working cycle should be greater than 10 minutes.
- Our company makes products with different specifications and special functions according to the requirements of users.



## Rui Du Mechanical and electrical (Shanghai) Co., Ltd



**TEL:** +86-021-68769756

**Contact:** Nico Zhou

**Position:** Sales Manager

**Email:** [sales@hvtesters.com](mailto:sales@hvtesters.com)

**Website:** [www.hvtesters.com](http://www.hvtesters.com)

**Mob/ WhatsApp:**

**+86-136 6190 8522**